

Add unbeatable flexibility and value to the PWRcell System by enabling whole home backup controlled via the user-friendly PWRview app. The PWRmanager enables data-driven efficient control of home loads to extend battery backup. This easy-to-install load management device integrates seamlessly with PWRcell, dramatically improving system performance.

FEATURES & BENEFITS

GENERAC

- Enhances PWRcell whole home backup
- · Flexibility and reliability during outages
- Turn home loads on and off on-the-fly with PWRview app
- Control up to twelve 120 V circuits or six 240 V circuits + two thermostats
- · Easy to install: no need for a new load panel

FEATURE	SPECIFICATIONS
NO. OF 120 V RELAYS	12
HVAC RELAYS	2
CURRENT RATING	60 Amps per relay
CONNECTIONS	WiFi, Ethernet
DIMENSIONS, L X W X H - IN (MM):	17.7" x 12.2" x 5.5" (449.58 x 309.88 x 139.7)
WEIGHT - LB (KG):	13.23 (5.2)
COMPLIANCE	UL-916, FCC Part 15 Class B, IC, Surge IEC 61000-4-5
ENCLOSURE	NEMA 3R
WIRE GAUGE	#14 to #6 AWG
OPERATING TEMPERATURE	-40°F to + 122°F (-40°C to + 50°C)
WARRANTY	10 YEAR LIMITED

Generac Power Systems, Inc. S45 W29290 Hwy. 59, Waukesha, WI 53189

www.Generac.com | 888-GENERAC (436-3722)

A0002198364 REV B

 $\ensuremath{\textcircled{O}}$ 2021 Generac Power Systems. All rights reserved. Specifications are subject to change without notice.







